



Specifications Osram LED Tube T8 SubstiTUBE PRO (EM/Mains) Standard Output 18.8W 3100lm - 865 Daylight | 150cm - Replaces 58W

[View Product](#)

## General Information

|                          |                                        |
|--------------------------|----------------------------------------|
| SKU                      | 242580                                 |
| EAN                      | 4058075612334                          |
| Brand                    | Osram                                  |
| Manufacturer Name        | LEDTUBE T8 EM PRO 1500 18,8W 865 OSRAM |
| Full box quantity        | 10                                     |
| Any Lamp all-in warranty | 5 Years                                |
| Energy efficiency class  | C                                      |
| Average Lifetime (h)     | 75000                                  |

## Technical Information

|                             |               |
|-----------------------------|---------------|
| Technology                  | LED           |
| Replaces (Watt)             | 58            |
| Wattage                     | 18.8          |
| Dimmable                    | Not Dimmable  |
| Cap / Base                  | G13           |
| Rotatable                   | No            |
| Colour Code                 | 865 Daylight  |
| Colour temperature (Kelvin) | 6500 Daylight |
| Colour Rendering (Ra)       | 80-89         |
| Colour of Light             | White         |

|                      |              |
|----------------------|--------------|
| Light colour options | Single Color |
|----------------------|--------------|

|                       |      |
|-----------------------|------|
| Luminous Flux (Lumen) | 3100 |
|-----------------------|------|

|                          |       |
|--------------------------|-------|
| Luminous Efficacy (lm/W) | 164.9 |
|--------------------------|-------|

|                       |             |
|-----------------------|-------------|
| Product Type Category | LED Tube T8 |
|-----------------------|-------------|

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Lamp Information

|                      |     |
|----------------------|-----|
| LED Starter included | Yes |
|----------------------|-----|

|                  |    |
|------------------|----|
| Requires Ballast | No |
|------------------|----|

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
|-----------------------|-----------------------------------------------------------------------|

|                 |                 |
|-----------------|-----------------|
| LED Tube Output | Standard Output |
|-----------------|-----------------|

|         |       |
|---------|-------|
| Housing | Glass |
|---------|-------|

|        |            |
|--------|------------|
| Series | Substitute |
|--------|------------|

## Dimensions

|        |       |
|--------|-------|
| Length | 150cm |
|--------|-------|

|             |      |
|-------------|------|
| Length (mm) | 1500 |
|-------------|------|

|               |      |
|---------------|------|
| Diameter (mm) | 26.7 |
|---------------|------|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

